# PEM49F35/6





# **Key Features**



### Subtle Design

This series' displays exhibit ultra narrow bezel design eliminating the visual superfluities, directing audience focus on your advertised content. This series is found to be desirable for digital signage specific design: internal usb cover, OPS-slot, detachable power plug, carrying handles and IR extender.



### **Built-in Connectivity**

This series features wired and wireless connectivity such as embedded WiFi and Bluetooth. Due to the wireless capabilities, the displays can easily gather its content without any external device. Moreover, WiFi allows screen sharing to be enjoyed with Miracast.



## **Daisy Chain**

The display can mirror the content (to another display) into its display port out coming from its display port in. This set up creates a daisy chain like structure allowing for monitors to be set up as Video Wall mode.



### **External Device Connections**

You may want to connect your teleconference system, screen sharing system, set-top box or external PCs via HDMI port. For this purposes, our monitors help you to maximize user experience with HDMI CEC (Consumer Electronics Control) and HDMI Hotplug capabilities.

# Display Control

Digital Signage Display SoC enables the users to control our displays using RS232 commands in a Local Area Network. Together with the full RS232 command list you can change/set volume, turn on/off the monitor, set a schedule for content display, set a webpage link to be displayed and give a wide range of commands in real-time.



### **OPS Support**

All our products in this series have compliance with OPS (Open Pluggable Standard). OPS will empower your screens with enhanced processing power and ability to choose Windows or Android as your operating system to fit your specific application.

### **Touch Support**

Our touch screens are compatible with this series. Infrared (IR) Touch Screens is designed to equip your current product with user-interactivity allowing the display to be smart display and many interactive applications to be enjoyed by the end users. The design also permits any person to overlay the touch screen on the display easily.

#### Signal Failover

Our SoC Software has a protection for "No Signal" scenario. If the USB is unplugged after your content is set to be displayed with USB, the display will either show your customized banner or search for any other signal from other sources (HDMI, Display Port, etc.). This failover protection is constructed for higher user experience.

### **Pixel Shifting**

Pixel Shifting is designed to be activated inside the SoC in order to prevent for potential risk of image sticking, caused by constant content. With this feature turned on, pixels on the screen will move in an interval while causing no interference of visual experience.

#### **Usb Auto-Play**

You will be able to show photo and video content automatically with USB Auto-play feature. SoC software gives you a choice to turn on USB auto-play function making it easy for end-users to show any media on the screen and not worry about anything else.

#### Auto Launch

We have made it easy to give any HTML5-based application link to the display within the SoC software. Upon this, the display will start with the given link. The application can either be an offline or an online application, allowing the customers to execute their own application.

#### Scheduler

Digital Signage Monitor Software allows many important features such as Scheduler. Scheduler sets your display turn on/off time easily and lets you not to worry about the status of your displays in any time.

#### **Operation Time Support**

Professional Panels used with this series are quality confirmed to operate 16 hours a day without any issues. Upon this, the series come with 400 Nits brightness levels suitable for medial indoor environment.

#### **Usb Security**

This series lets your USB and your content to be secured within the back cover of the display. The cover is protected with a screw not allowing any outside intervention.

### Source Switching

It is made available to set any Source on startup of the display. It can also be switched on any other signal source using scheduler and failover scenarios. This lets the users to freely control the process of their requirements allowing best user experience.

# PEM49F35/6



### PANEL

Size Brightness (Cd / M2) Panel Type Resolution Orientation Contrast Ratio Dynamic Constrast Ratio Panel Life Time ( Typ. ) Response Time Areas of Usage Backlight Type Panel Technology Front Type Active Area Viewing Angle Color Value Screen Treatment Haze Level (%) H-Freq Max. Pixel Freq. V-Freq

## INPUTS

| HDMI              | YES     |
|-------------------|---------|
| HDMI Support Type | 2 × 2.0 |
| USB 2.0           | YES     |
| USB 3.0           | YES     |
| RS232             | YES     |
| RJ12              | YES     |
| Remote Extender   | YES     |
| RCA (L/R)         | YES     |
| YPbPr             | YES     |
| VGA               | YES     |
|                   |         |

49"

24/7

1200:1 40000:1

50000 Hr

9 ms

Indoor

IPS UNB

178°

<2

67.5KHz

78MHz

60Hz

Edge LED

1074 x 605 (HxV)

8 Bit, 16.7 M Colors

3H - Hard Coating

400 cd/m2

1920 x 1080(16:9) - FHD

Horizontal/Vertical

## MECHANICAL

| Product Dimensions (mm) | 1097 x 69 x 630 mm (WxDxH) |
|-------------------------|----------------------------|
| Product Weight (kg)     | 15,6                       |
| Package Dimensions      | 1215 x 165 x 775 (WxDxH)   |
| Package Weight(kg)      | 19,8                       |
| Vesa Mounting (mm)      | 200 x 200                  |
| Bezel Width (mm)        | 8 x 8 x 12 (TxR/LxB)       |
|                         |                            |

### POWER

Power Supply Power Consumption(Stand-By) 110 VAC - 240 VAC - 50/60 Hz ≼0.5W

### DISPLAY INFO FEATURES

| Set ID               | YES |
|----------------------|-----|
| Software Upgrade     | YES |
| Serial Number Access | YES |
| Model Name Access    | YES |
| Lifetime Display     | YES |
|                      |     |

## POWER UP FEATURES

| Power Up Mode Selection         | YES |
|---------------------------------|-----|
| Quick Standby                   | YES |
| Delayed Power Up                | YES |
| Auto Launch                     | YES |
| HDMI Wakeup                     | YES |
| HDMI CEC                        | YES |
| Power Up Picture Mode Selection | YES |
|                                 |     |

### MAINBOARD

Mainboard Model

17MB120DS-R4

### OUTPUTS

| HDMI              | YES |
|-------------------|-----|
| Mini Jack (Audio) | YES |
| RCA (L/R)         | YES |
| Speakers          | YES |
| Speakers output   | YES |
| Headphone         | YES |
|                   |     |

### WORKING CONDITIONS

| Temperature Conditions | +40°C/0°C |
|------------------------|-----------|
| Humidity               | 0 to 90%  |

### CONNECTIVITY FEATURES

| Embedded WiFi           | YES |
|-------------------------|-----|
| Embedded Bluetooth      | YES |
| Wireless Screen Casting | YES |

### CONTROL FEATURES

| On Screen Menu Rotation   | YES |
|---------------------------|-----|
| Image Sticking Protection | YES |
| No Signal Power Off       | YES |
| No Signal Screen Saver    | YES |
| Auto Source Switch        | YES |
| Panel Button Lock         | YES |
| Remote Controller Lock    | YES |
| Device Control over RS232 | YES |
| Device Control over LAN   | YES |
| Crestron Support          | YES |
| Auto Color Alignment      | YES |

# USB FEATURES

| USB Cloning   |  | YES |
|---------------|--|-----|
| USB SW Update |  | YES |
| USB Lock      |  | YES |
| Auto Play     |  | YES |
| Video Support |  | YES |
| Photo Support |  | YES |
| Audio Support |  | YES |
|               |  |     |

# MULTI DISPLAY FEATURES

| Videwall Tiling support | YES |
|-------------------------|-----|
| HDCP Support            | YES |
| HDMI Daisy Chain        | YES |
| DP Daisy Chain          | YES |
|                         |     |

# WEB LINK FEATURES

| HTML5 API Support            | YES |
|------------------------------|-----|
| Default browser page setting | YES |
| NTP server setting           | YES |
| Auto CMS webpage setting     | YES |
| Unicast Support              | YES |
| Multicast support            | YES |
|                              |     |

## MECHANICAL FEATURES

| Rocker Switch          | YES |
|------------------------|-----|
| Joystick Buttons       | YES |
| IR Extender Support    | YES |
| Detachable power cable | YES |
| Carrying slots/handles | YES |
| Internal usb cover     | YES |
| OPS Slot               | YES |
|                        |     |

## SCHEDULER SETTINGS

| Power-up Time Setting   | YES |
|-------------------------|-----|
| Power-down Time Setting | YES |
| Power-up Source Setting | YES |
| Activate Days Setting   | YES |
| Real Time Clock (RTC)   | YES |
|                         |     |

# VOLUME CONTROL FEATURES

| Volume Limit Setting   | YES |
|------------------------|-----|
| Startup Volume Setting | YES |
| Volume Fixing          | YES |

# ACCESSORIES

| Wall Mount Kit              | YES |
|-----------------------------|-----|
| Remote Controller           | YES |
| Remote Controller Batteries | YES |
| User Manual                 | YES |
| Quick Start Guide           | YES |
| IR Extender Cable           | YES |
| Power Cord                  | YES |
| Cable Management Clips      | YES |
| USB Security Cover          | YES |
|                             |     |

## CERTIFICATION

| Safety | YES |
|--------|-----|
| EMC    | YES |
| CB     | YES |
| CE     | YES |
|        |     |